



# ARQ100 REMOTE

## USERS MANUAL




### Basic Instructions:

1. Open the battery covers on the back of the keyboard, remove the USB receiver



2. Insert 2 x AAA batteries



3. Plug the remote receiver into the USB of the BuzzTV Box

4. Make sure your Buzz TV box is connected and is working on your TV

5. You can now use the ARQ100 remote with your TV

### Learning Remote Feature

Learning methods please see as below:

- A.** Press and hold "Power" + "OK" more than 3 seconds, the LED will be turned on, indicates the remote enters learning mode.
- B.** Align the IR tube of the remote control with the IR tube of the remote control which needs to be learned within 3cm.
- C.** Press the "TV Power" button on the remote control, the LED will change from long light to slow flashing, waiting to receive the learning signal. Press the button of the remote control which needs to be learned and keep it sending the IR code. When the remote controller receives the learning signal, the LED flashes 3 times and then long light, indicating that the learning signal is received.
- D.** Repeat **step C** to learn "Source" key.
- E.** Press the "OK" key, then the LED turned off, indicates the code has been save and exit the learning mode.

### How to Repair the ARQ100 USB Dongle

If you feel that the TV is not receiving any air mouse or keyboard inputs, it is possible that the USB dongle is not paired properly with the remote.

Please follow the steps below to repair them again:

- Press OK button + VOD button for 3 seconds until the LED lights up
- RCU enters Pairing Mode, keep the distance between the RCU and the USB dongle within 30cm,
- Insert the USB dongle into the BuzzTV Box
- LED will flash 3 times and then turn off. This should mean that the pairing was a success

### How To Use It As Air Mouse

- The Air Mouse pointer function is set to "OFF" by default
- Press the **FN** button to activate the mouse pointer function
- Swing your wrist to form any easy and smooth motion
- To select an item, take the cursor to the icon and press the left key

To use the back keyboard, simply go to the field you need to enter the text, press the left key and start typing.

### Turn Off The Air Mouse Mode

If you do not use any air mouse keys for 30 seconds, it will go to sleep

If you want to turn it off quicker, you need to press the left/right arrow keys above the cursor key

To activate the air mouse, please press the cursor key again.

### How To Recalibrate The Air Mouse

If the cursor begins to drift, please follow the instructions below to recalibrate it.

- Put the remote on a flat surface
- Press and hold **ESC** + **FN** on the keyboard together until the **FN** LED light comes on
- The **FN** LED light should turn off in 5 seconds
- It means recalibration is successful



- |                 |   |                          |
|-----------------|---|--------------------------|
| ① Power Button  | ⑮ Navigation Keys                             | ⑳ Capitals Lock (CAP LK) |
| ② STB - Standby | ⑯ Faves                                       | ㉑ Function (FN)          |
| ③ Source        | ⑰ Server                                      | ㉒ Function LED (FN LED)  |
| ④ Volume / Mute | ⑱ Live TV                                     | ㉓ Escape (ESC)           |
| ⑤ Search        | ⑲ Video On Demand (VOD)                       | ㉔ Enter                  |
| ⑥ Number Keys   | ㉑ TV Series                                   | ㉕ Backspace / Delete     |
| ⑦ Page Down     | ㉒ Volume Up / Down                            |                          |
| ⑧ Page Up       | ㉓ Channel Up / Down                           |                          |
| ⑨ Last          | ㉔ Rewind / Play - Pause / Fast Forward / Stop |                          |
| ⑩ Info          | ㉕ Home  |                          |
| ⑪ Air Mouse     | ㉖ Android Settings                            |                          |
| ⑫ Menu          | ㉗ Record                                      |                          |
| ⑬ Guide         | ㉘ PVR   |                          |
| ⑭ Last          |   |                          |